

|              |              |
|--------------|--------------|
| Issued:      | October 1997 |
| Status:      | Standard     |
| X11 Release: | 23           |

---

## LD 81: Features and Station Print

---

Overlay program 81 is used to print a list or count of telephones with selected features. It also allows last service change date information to be printed.

In Release 18, a TN which is the Multiple Appearance Redirection Prime (MARP) is indicated by an "M" following FEAT (when TYPE = MCN, SCN, MCR, or SCR).

## Prompts and responses

| Prompt                   | Response    | Comment                                                                         |
|--------------------------|-------------|---------------------------------------------------------------------------------|
| REQ                      | aaa         | Request (aaa = LST, CNT, or END)                                                |
| CUST                     | xx xx       | One Customer or a range of Customer numbers                                     |
| DATE                     | a...a       | Print data from activity date specified (You may enter :<br>dd mmm yyyy or ACT) |
| PAGE                     | (NO) YES    | Data printed on a per page basis                                                |
| DES                      | d...d       | 1-6 alphanumeric character Office Data Administration<br>System                 |
| FEAT                     | aaaa        | Features requested (FEAT responses begin on<br>page 827)                        |
| SGRP                     | 0-999 0-999 | Station Group                                                                   |
| RNPG                     | xx yy       | Ringling Number Pick Up Group                                                   |
| LSNO                     | xx yy       | List Number                                                                     |
| NCOS                     | xx yy       | Network Class of Service                                                        |
| - ADJUST PAPER THEN <cr> | <cr>        | Starts printing                                                                 |
| NACT                     | (NO) YES    | Next Activity                                                                   |

## Alphabetical list of prompts

| Prompt            | Response                             | Comment                                                                                                                                                                                                                                                                 | Pack/Rel                               |
|-------------------|--------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------|
| ADJUST PAPER THEN | <cr>                                 |                                                                                                                                                                                                                                                                         | basic-1                                |
|                   | <cr>                                 | Starts printing<br>Prompted when PAGE = YES                                                                                                                                                                                                                             |                                        |
| CUST              | xx xx<br><cr>                        | One Customer or a range of Customer numbers<br>All Customers                                                                                                                                                                                                            | basic-1                                |
| DATE              | dd mmm yyyy                          | Print data from activity date specified. Where: <ul style="list-style-type: none"> <li>• dd = day (0-31)</li> <li>• mmm = month (JAN-DEC)</li> <li>• yyyy = year</li> </ul>                                                                                             | basic-1                                |
|                   | ACT<br><cr>                          | Print data from last Activity date.<br>Disregard date restrictions.                                                                                                                                                                                                     |                                        |
| DES               | d...d<br><br>dddd<br>d+<br>+<br><cr> | 1-6 alphanumeric character Office Data Administration System (ODAS) Station Designator<br>Print data for stations with specific DES.<br>Print data for stations with a DES starting with d.<br>Print data for all stations with no DES.<br>Print data for all stations. | odas-1                                 |
| FEAT              |                                      | Features requested<br><br>Enter a specific feature mnemonic or one the following for groups of features: ALL, COS, DNK, SETS, SCL, RNP or 500.<br><br>FEAT is repeated until <cr> is entered.                                                                           | basic-1                                |
|                   | 2000<br>3000<br>4020<br>500          | All M2000 telephones<br>M3000 Touchphone<br>M4020 telephone (no longer supported)<br>500/2500 type telephone                                                                                                                                                            | dset-7<br>tset-7<br>basic-8<br>basic-1 |
|                   |                                      | Print both MNL and DIP telephones. 2500 type telephones are requested by DTN entry.                                                                                                                                                                                     |                                        |

# LD 81

| Prompt | Response | Comment                                                                                                                                                                      | Pack/Rel |
|--------|----------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------|
| AAA    |          | Automatic Answerback Allowed                                                                                                                                                 | aab-1    |
| AAD    |          | Automatic Answerback Denied                                                                                                                                                  |          |
| AAG    |          | Answer call from Agent key                                                                                                                                                   |          |
| AAK    |          | Automatic Answerback Key                                                                                                                                                     | aab-1    |
| ABDA   |          | Abandoned call record and time to answer Allowed                                                                                                                             | supp-18  |
| ABDD   |          | Abandoned call record and time to answer Denied                                                                                                                              |          |
| ACD    |          | ACD in calls key                                                                                                                                                             | bacd-1   |
| ACNT   |          | Assignment of activity codes allowed                                                                                                                                         | bacd-13  |
| ADD    |          | Automatic Digit Display equipped                                                                                                                                             | ddsp-1   |
| ADL    |          | Autodial key                                                                                                                                                                 | optf-1   |
| ADV    |          | Data port Verification allowed                                                                                                                                               | bacd-5   |
| AGN    |          | ACD Agent                                                                                                                                                                    | bacd-1   |
| AGT    |          | ACD Agent's key                                                                                                                                                              |          |
| AGTA   |          | ACD services for 500/2500 telephone Allowed                                                                                                                                  | bacd-16  |
| AGTD   |          | ACD services for 500/2500 telephone Denied                                                                                                                                   |          |
| AHA    |          | Automatic Hold Allowed                                                                                                                                                       | supp-10  |
| AHD    |          | Automatic Hold Denied                                                                                                                                                        |          |
| ALL    |          | All features                                                                                                                                                                 | basic-1  |
|        |          | When REQ = LST, only the features actually programmed on telephones are listed along with the associated TN. Features not listed are RNPK, DIP and MNL.                      |          |
|        |          | When REQ = CNT, features available in the system software are listed even if they are not programmed on any telephone. Not listed are RNPK, 500, 2500, SL-1, 2000, and 3000. |          |
| AMG    |          | ACD Answer/Monitor Emergency call key                                                                                                                                        | supp-14  |
| AO3    |          | Three-party conference key                                                                                                                                                   | basic-1  |
| AO6    |          | Six-party conference key                                                                                                                                                     |          |

| Prompt | Response | Comment                                  | Pack/Rel |
|--------|----------|------------------------------------------|----------|
|        | ARC      | Attendant Recall key                     | basic-1  |
|        | ARHA     | Audible Reminder of Held Call Allowed    | basic-14 |
|        | ARHD     | Audible Reminder of Held Call Denied     |          |
|        | ASCA     | Alarm Security Allowed                   | ohas-18  |
|        | ASCD     | Alarm Security Denied                    |          |
|        | ASP      | ACD Answer Supervisor call key           | iani-14  |
|        | ATW      | ACD Call Waiting time indication key     |          |
|        | AUTD     | Authorization Code Denied                | ssau-19  |
|        | AUTR     | Authorization Code Restricted            |          |
|        | AUTU     | Authorization Code Unrestricted          |          |
|        | AWC      | ACD Calls Waiting display key            |          |
|        | BFS      | Busy Forward Status key                  | bfs-20   |
|        | BNRA     | Busy Number Redial Allowed               | ffc-21   |
|        | BNRD     | Busy Number Redial Denied                |          |
|        | C6A      | Six-Party Conference Allowed             | basic-10 |
|        | C6D      | Six-Party Conference Denied              |          |
|        | CA       | Combined No Hold Conference and Autodial | basic-14 |
|        | CAS      | Centralized Attendant Service            | casm-1   |
|        | CCBA     | Collect Call Blocking Allowed            | ccb-21   |
|        | CCBD     | Collect Call Blocking Denied             |          |
|        | CCOS     | Controlled Class of Service key          | ccos-7   |
|        | CCSA     | Controlled Class of Service Allowed      |          |
|        | CCSD     | Controlled Class of Service Denied       |          |
|        | CDCA     | Conferee Display Count Allowed           | basic-23 |
|        | CDCD     | Conferee Display Count Denied            |          |
|        | CDMA     | Station Activity Records Allowed         | mct-20   |
|        | CDMD     | Station Activity Records Denied          |          |
|        | CFHA     | List/count sets with CFHA CLS            | cfho-20  |
|        | CFHD     | List/count sets with CFHD CLS            |          |

# LD 81

| Prompt | Response     | Comment                                                                                                                                                                                                           | Pack/Rel |
|--------|--------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------|
|        | CFTA<br>CFTD | Call Forward by Call Type Allowed<br>Call Forward by Call Type Denied                                                                                                                                             | basic-10 |
|        | CFW          | Call Forward key                                                                                                                                                                                                  | basic-1  |
|        | CFXA<br>CFXD | Call Forward number to External DN Allowed<br>Call Forward number to External DN Denied                                                                                                                           | basic-10 |
|        | CHD          | Combined No Hold Conference and Direct Hot Line                                                                                                                                                                   | basic-14 |
|        | CHG          | Charge Account key                                                                                                                                                                                                | fca-1    |
|        | CHL          | Combined No Hold Conference and Hot Line list                                                                                                                                                                     | basic-14 |
|        | CLTA<br>CLTD | Network Call Trace Allowed<br>Network Call Trace Denied                                                                                                                                                           | basic-17 |
|        | CMSA         | Command and Status link Allowed                                                                                                                                                                                   | csi-8    |
|        | CNDA<br>CNDD | Call Party Name Display Allowed<br>Call Party Name Display Denied                                                                                                                                                 | cpnd-10  |
|        | CNIA<br>CNID | Call Number Identification Allowed<br>Call Number Identification Denied                                                                                                                                           | pra-12   |
|        | CNTA<br>CNTD | Network ACD Countdown Allowed<br>Network ACD Countdown Denied                                                                                                                                                     | nacd-15  |
|        | COS          | Print stations with Class of Service restrictions.<br>These are telephones with equipped with C6A, C6D,<br>CMSA, CNDA, CNDD, CTD, CUN, DSI, FRE, FR1,<br>FR2, NCOS, SFA, SFD, SRE, TLD, TTA, TTD, UNR and<br>VMA. | basic-1  |
|        | CPFA<br>CPFD | Forced Camp-On from another set Allowed<br>Forced Camp-On from another set Denied                                                                                                                                 | povr-15  |
|        | CPN          | Display Calling Party Number key                                                                                                                                                                                  | cpnd-10  |
|        | CPTA<br>CPTD | Forced Camp-On to another set Allowed<br>Forced Camp-On to another set Denied                                                                                                                                     | ffc-15   |
|        | CRA          | Continuous Ring Allowed                                                                                                                                                                                           | basic-14 |

| Prompt | Response | Comment                                               | Pack/Rel  |
|--------|----------|-------------------------------------------------------|-----------|
|        | CRD      | Continuous Ring Denied                                |           |
|        | CS       | Combined No Hold Conference and Speed Call            |           |
|        | CSD      | Conferee Selectable Display key                       | basic- 23 |
|        | CTD      | Conditionally Toll Denied                             | basic-1   |
|        | CUN      | Conditionally Unrestricted                            |           |
|        | CWA      | Call Waiting Allowed                                  | basic-1   |
|        | CWD      | Call Waiting Denied                                   |           |
|        | CWT      | Call Waiting key                                      |           |
|        | DAG      | ACD Display Agents key                                | bacd-1    |
|        | DCFw     | Default call forward for Phantom TNs                  | phtn-20   |
|        | DDGA     | DN Display on other set Allowed                       | sdd-21    |
|        | DDGD     | DN Display on other set Denied                        |           |
|        | DDS      | Digit Display allowed                                 | ddsp-1    |
|        | DDV      | Data port Verification denied                         | amp-5     |
|        | DELA     | Dealer Allowed                                        | ohol-20   |
|        | DELD     | Dealer Denied                                         |           |
|        | DIG      | Dial Intercom Group                                   | di-1      |
|        | DIP      | Dial Pulse telephone (500 type)                       | bssic-1   |
|        | DLO      | Digital Long line COS                                 | ftc-16    |
|        | DNAA     | ANI DN used as the customer Listed Directory number   | cist-21   |
|        | DNAD     | Outgoing CDTI2/CSDTI2 route used as DN in ANI message |           |
|        | DNDA     | Dialed Name Display Allowed                           | cpnd-13   |
|        | DNDD     | Dialed Name Display Denied                            |           |
|        | DNK      | Telephones with MCN, MCR, SCN, and SCR keys           | basic-1   |
|        | DPU      | DN Pickup key                                         | grp-1     |
|        | DPUA     | DN Pickup Allowed                                     | dcp-12    |

# LD 81

Page 832 of 1004     Alphabetical list of prompts

---

| Prompt | Response | Comment                                           | Pack/Rel       |
|--------|----------|---------------------------------------------------|----------------|
|        | DPUD     | DN Pickup Denied                                  |                |
|        | DRC      | DID Route Control                                 | basic-14       |
|        | DRG1     | Digital telephone Distinctive Ringing (high/fast) | drng-7         |
|        | DRG2     | Digital telephone Distinctive Ringing (high/slow) |                |
|        | DRG3     | Digital telephone Distinctive Ringing (low/fast)  |                |
|        | DRG4     | Digital telephone Distinctive Ringing (low/slow)  |                |
|        | DSH      | Digital Short line COS                            | ftc-16         |
|        | DSI      | Data Service access or IS Server TN allowed       | xcti-16        |
|        | DSP      | Digit Display key                                 | ddsp-1         |
|        | DTA      | Data set                                          | basic-5        |
|        | DTN      | Digitone dial telephone (2500 type)               | basic-1        |
|        | DWC      | ACD Display Waiting Calls key                     | bacd-1         |
|        | ENG      | English language display for M2317                | dlt2-12        |
|        | EOVR     | Enhanced Override key                             | povr-15        |
|        | FAXS     | Facsimile servers                                 | faxs-18        |
|        | FBA      | Call Forward Busy Allowed                         | optf-1         |
|        | FBD      | Call Forward Busy Denied                          |                |
|        | FITA     | Flexible Incoming Tones Allowed                   | basic-14       |
|        | FITD     | Flexible Incoming Tones Denied                    |                |
|        | FLXA     | Flexible voice/data TN allowed                    | digital_set-22 |
|        | FLXD     | Flexible voice/data TN denied                     |                |
|        | FNA      | Call Forward No Answer Allowed                    | basic-1        |
|        | FND      | Call Forward No Answer Denied                     |                |
|        | FR1      | Fully Restricted class 1                          | basic-1        |
|        | FR2      | Fully Restricted class 2                          |                |
|        | FRE      | Fully Restricted                                  |                |
|        | FRN      | French language display for M2317                 | dlt2-12        |



| Prompt | Response     | Comment                                                                        | Pack/Rel |
|--------|--------------|--------------------------------------------------------------------------------|----------|
|        | GHD          | Group Hunt Denied key                                                          | grp-1    |
|        | GPU          | Group Call Pickup key                                                          | dcp-12   |
|        | GPUA<br>GPUD | Group call Pickup Allowed<br>Group call Pickup Denied                          | dcp-12   |
|        | GRC          | Group Recall key                                                               | grp-1    |
|        | HBTA<br>HBTD | Hunt by call Type Allowed<br>Hunt by call Type Denied                          | supp-10  |
|        | HFA<br>HFD   | Handsfree Allowed M2616<br>Handsfree Denied M2616                              | arie-14  |
|        | HLD          | LOGIVOX Telephone Hold key                                                     | supp-10  |
|        | HOTD<br>HOTL | Enhanced Hot Line, Direct entry method<br>Enhanced Hot Line, List entry method | hot-10   |
|        | HPR          | High Priority station                                                          | basic-1  |
|        | HSPA<br>HSPD | Hospitality Management Allowed<br>Hospitality Management Denied                | hosp-16  |
|        | HTA<br>HTD   | Hunting Allowed<br>Hunting Denied                                              | basic-1  |
|        | HTL          | Hot Line                                                                       | hot-10   |
|        | IAMA         | ICP Answering Machine Denied/Allowed                                           | icp-16   |
|        | ICDA<br>ICDD | Internal CDR Allowed<br>Internal CDR Denied                                    | icdr-10  |
|        | ICF          | Internal Call Forward key                                                      | icf-19   |
|        | IMA          | IMS or IVMS Allowed                                                            | ims-2    |
|        | IMM          | Immediate                                                                      | xct1-16  |
|        | IPNA         | Intercept Position Allowed                                                     | icp-14   |
|        | IRA          | Incoming Ringing line preference Allowed                                       | 1sel-4   |

# LD 81

| Prompt | Response                             | Comment                                                                                                                                                                                          | Pack/Rel       |
|--------|--------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------|
|        | IRD                                  | Incoming Ringing line preference Denied                                                                                                                                                          |                |
|        | IRGA                                 | Interrogation Set Allowed                                                                                                                                                                        | icp-14         |
|        | ITGE                                 | Incoming Trunk Group Exclusion                                                                                                                                                                   | baut-10        |
|        | KLS                                  | Key/lamp Strip                                                                                                                                                                                   | basic-1        |
|        | LDN                                  | Listed Directory Number (DN)<br><b>Note:</b> LDN does not apply for Release 22.                                                                                                                  | dldn-12        |
|        | LDTA<br>LDTD                         | Line Disconnect Tone allowed<br>Line Disconnect Tone denied                                                                                                                                      | basic-17       |
|        | LED                                  | LED state for ACD agents                                                                                                                                                                         | supp-10        |
|        | LLC1<br>LLC2<br>LLC3<br>LLCA<br>LLCN | Line Load Control level 1<br>Line Load Control level 2<br>Line Load Control level 3<br>Line Load Control Allowed<br>Line Load Control off                                                        | 11c-10         |
|        | LNA<br>LND<br>LNK                    | Last Number Redial Allowed<br>Last Number Redial Denied<br>Last Number Redial Key                                                                                                                | 1nr-8          |
|        | LOL                                  | Long Line Class of Service                                                                                                                                                                       | xops-20        |
|        | LPA<br>LPD                           | Message Waiting lamp Allowed<br>Message Waiting lamp Denied                                                                                                                                      | mwc-1<br>mwc-1 |
|        | LPR                                  | Low Priority station                                                                                                                                                                             | basic-1        |
|        | LSPK                                 | Loudspeaker key                                                                                                                                                                                  | ohol-20        |
|        | LVXA<br>LVXD                         | LOGIVOX Telephone Allowed<br>LOGIVOX Telephone Denied                                                                                                                                            | supp-10        |
|        | (MBXD)<br>MBXA                       | Multi-Party Operation (MPO) Blind Transfer Denied.<br>Multi-Party Operation (MPO) Blind Transfer Allowed.<br>Multi-Party Operations (MPO) package 141 must be<br>equipped to enter MBXD or MBXA. | mpo-21         |

| Prompt | Response | Comment                                                                                                                                    | Pack/Rel |
|--------|----------|--------------------------------------------------------------------------------------------------------------------------------------------|----------|
|        | MCD      | Message Center DN                                                                                                                          | mwc-1    |
|        | MCK      | Message Cancellation Key                                                                                                                   |          |
|        | MCN      | Multiple Call Non-Ringing DN                                                                                                               | basic-1  |
|        |          | In Release 18, a TN which is the Multiple Appearance Redirection Prime (MARF) for the DN is indicated by an "M" in the output (MCN M).     |          |
|        | MCR      | Multiple Call Ringing DN                                                                                                                   | basic-1  |
|        |          | In X11 Release 18, a TN which is the Multiple Appearance Redirection Prime (MARF) for the DN is indicated by an "M" in the output (MCN M). |          |
|        | MCRA     | Multiple Call Arrangement Allowed                                                                                                          | supp-15  |
|        | MCRD     | Multiple Call Arrangement Denied                                                                                                           |          |
|        | MCTA     | Malicious Call Trace Allowed                                                                                                               | mct-10   |
|        | MCTD     | Malicious Call Trace Denied                                                                                                                | mct-19   |
|        | MIK      | Message Indication Key                                                                                                                     | mwc-1    |
|        | MINA     | Message Intercept Allowed                                                                                                                  | mint-15  |
|        | MIND     | Message Intercept Denied                                                                                                                   |          |
|        | MNL      | Manual service                                                                                                                             | basic-1  |
|        | MON      | TN(s) Monitored by at least one BFS key                                                                                                    | bfs-20   |
|        | MRA      | Message Registration Allowed                                                                                                               | mr-10    |
|        | MRD      | Message Registration Denied                                                                                                                |          |
|        | MSB      | Make Set Busy key                                                                                                                          | msb-1    |
|        | MTA      | Maintenance set Allowed                                                                                                                    | basic-1  |
|        | MWA      | Message Waiting Allowed                                                                                                                    | mwc-1    |
|        | MWD      | Message Waiting Denied                                                                                                                     |          |
|        | MWK      | Message Waiting key                                                                                                                        |          |
|        | NAMA     | Name display on other set Allowed                                                                                                          | sdd-21   |
|        | NAMD     | Name display on other set Denied                                                                                                           |          |
|        | NCOS     | Network Class of Service (COS)                                                                                                             | ncos-1   |
|        | NDD      | No Digit Display                                                                                                                           | ddsp-1   |

# LD 81

Page 836 of 1004     Alphabetical list of prompts

---

| Prompt | Response | Comment                                                                                                                 | Pack/Rel |
|--------|----------|-------------------------------------------------------------------------------------------------------------------------|----------|
|        | NHC      | No Hold Conference                                                                                                      | basic-14 |
|        | NIA      | Incoming non-ringing line preference Allowed                                                                            | 1se1-4   |
|        | NID      | Incoming non-ringing line preference Denied                                                                             | 1se1-4   |
|        | NKL      | Notification Key Lamps                                                                                                  | drng-7   |
|        | NRCA     | Forced Camp-On night class restriction Allowed                                                                          | supp-16  |
|        | NRCD     | Forced Campon night class restriction Denied                                                                            |          |
|        | NRD      | ACD Not Ready key                                                                                                       | bacd-1   |
|        | NROA     | Priority override night class restriction Allowed                                                                       | supp-16  |
|        | NROD     | Priority override night class restriction Denied                                                                        |          |
|        | NRWA     | Call Waiting Night class restriction Allowed                                                                            | supp-16  |
|        | NRWD     | Call Waiting Night class restriction Denied                                                                             |          |
|        | NSVC     | ACD Night Service key for Supervisor Control                                                                            | bacd-12  |
|        | OBV      | ACD Observe agent key                                                                                                   |          |
|        | OCBA     | Outgoing Call Barring Allowed                                                                                           | ccb-21   |
|        | OCBD     | Outgoing Call Barring Denied                                                                                            |          |
|        | OLA      | Outgoing Line preference Allowed                                                                                        | 1se1-4   |
|        | OLD      | Outgoing Line preference Denied                                                                                         |          |
|        | ONP      | On Premise extension (X11 Release 19 & earlier)                                                                         | basic-1  |
|        | ONS      | On Premise Station (X11 Release 20 & later)                                                                             | xops-20  |
|        | OPS      | Off Premise Station (X11 Release 20 & later)                                                                            | xops-20  |
|        | OPX      | Off Premise extension (X11 Release 19 & earlier)                                                                        | basic-1  |
|        | OSN      | On Site Notification key.<br>OSN is accepted as valid input only if the system is ESA<br>and ESA_SUPP package equipped. | esa- 23  |
|        | OVB      | Attendant Overflow position                                                                                             | aop-1    |
|        | OVDA     | Override Allowed (500/2500 telephone)                                                                                   | ffc-15   |
|        | OVDD     | Override Denied (500/2500 telephone)                                                                                    |          |
|        | OVR      | Override key                                                                                                            | basic-1  |

| Prompt | Response       | Comment                                                                   | Pack/Rel   |
|--------|----------------|---------------------------------------------------------------------------|------------|
|        | PDN            | Prime Directory Number<br><b>Note:</b> LDN does not apply for Release 22. | pra-12     |
|        | (PGND)<br>PGNA | Deny PAGENET access<br>Allow PAGENET access                               | pagenet-22 |
|        | PHD            | Permanent Hold                                                            | basic-4    |
|        | POA<br>POD     | Optional Privacy Allowed<br>Optional Privacy Denied                       | basic-1    |
|        | PRK            | Park key                                                                  | cprk-2     |
|        | PRS            | Privacy Release key                                                       | basic-1    |
|        | PRSA<br>PRSD   | Priority Call Pickup Allowed<br>Priority Call Pickup Denied               | supp-15    |
|        | PUA<br>PUD     | Call Pickup Allowed<br>Call Pickup Denied                                 | grp-1      |
|        | PVN<br>PVR     | Private Line Non-ringing phantom DN<br>Private Line Ringing phantom DN    | basic-1    |
|        | RAG            | ACD Call Agent key                                                        |            |
|        | RCC            | Restricted from Receiving Collect Calls                                   | supp-10    |
|        | RCK            | Ringing Change Key                                                        | rck-15     |
|        | RDI            | Restricted from receiving DID calls                                       | supp-10    |
|        | RDL            | Stored Number Redial                                                      | basic-14   |
|        | RDLA<br>RDLD   | Automatic Redial call Allowed<br>Automatic Redial call Denied             | ardl-22    |
|        | RGa            | Ring Again key                                                            | optf-1     |
|        | RLFA<br>RLFD   | Reversed Lamp Flash Allowed<br>Reversed Lamp Flash Denied                 | supp-10    |
|        | RLS            | Release key                                                               | basic-1    |

# LD 81

Page 838 of 1004     Alphabetical list of prompts

| Prompt | Response     | Comment                                                                                                                                                                  | Pack/Rel |
|--------|--------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------|
|        | RNP          | Ringin Number Pickup (includes PUA, PUD and RNPK)                                                                                                                        | grp-1    |
|        | RNPK         | Ringin Number Pickup key                                                                                                                                                 | grp-1    |
|        | RPA          | Radio Paging Allowed                                                                                                                                                     | rpa-15   |
|        | RTDA<br>RTDD | Call Redirection by Time of day allowed<br>Call Redirection by Time of day denied                                                                                        | basic-22 |
|        | SAR          | Scheduled Access Restriction                                                                                                                                             | sar-20   |
|        | SCC          | Speed Call Controller                                                                                                                                                    | optf-1   |
|        | SCI          | Station Category Indication Priority Level                                                                                                                               | sci-7    |
|        | SCL          | Speed Call (includes SCU and SCC)                                                                                                                                        | optf-1   |
|        | SCN          | Single Call Non-ringing DN<br><br>In Release 18, a TN which is the Multiple Appearance Redirection Prime (MARF) for the DN is indicated by an "M" in the output (MCN M). | basic-1  |
|        | SCR          | Single Call Ringing DN<br><br>In Release 18, a TN which is the Multiple Appearance Redirection Prime (MARF) for the DN is indicated by an "M" in the output (MCN M).     | basic-1  |
|        | SCU          | Speed Call User                                                                                                                                                          | optf-1   |
|        | SETS         | All telephones                                                                                                                                                           | basic-1  |
|        | SFA<br>SFD   | Second level Forwarding Allowed<br>Second level Forwarding Denied                                                                                                        | optf-10  |
|        | SHL          | Short Line Class of Service                                                                                                                                              | xops-20  |
|        | SIG          | Buzz key to phantom DN                                                                                                                                                   | basic-1  |
|        | SL1          | SL-1 stations                                                                                                                                                            | basic-1  |
|        | SMSA<br>SMSD | Standalone Mail Server Allowed<br>Standalone Mail Server Denied                                                                                                          | samm-20  |

| Prompt | Response     | Comment                                                                                                         | Pack/Rel           |
|--------|--------------|-----------------------------------------------------------------------------------------------------------------|--------------------|
|        | SNR          | Stored Number Redial                                                                                            | ffc-15             |
|        | SPKA<br>SPKD | Speaker Class of Service Allowed<br>Speaker Class of Service Denied                                             | ohol-20            |
|        | SPV          | ACD Supervisor                                                                                                  | acdb-1             |
|        | SRE          | Semi-Restricted                                                                                                 | basic-1            |
|        | SSC<br>SSU   | System Speed Call Controller<br>System Speed Call User                                                          | optf-1             |
|        | SWA<br>SWD   | Station-to-Station Call Waiting Allowed<br>Station-to-Station Call Waiting Denied                               | basic-8            |
|        | TAD          | Time And Date key                                                                                               | ddsp-1             |
|        | TDD          | Touchphone Display                                                                                              | tset-7             |
|        | THF<br>THFA  | Centrex Trunk Switchhook Flash<br>Centrex Trunk Switchhook Flash Allowed (500/2500<br>telephones)               | thf-14             |
|        | THFD         | Centrex Trunk Switchhook Flash Denied (500/2500<br>telephones)                                                  |                    |
|        | TLD          | Toll Denied                                                                                                     | basic-1            |
|        | TRC          | Malicious Call Trace key                                                                                        | mct-10             |
|        | TRN          | Call Transfer key                                                                                               | basic-1            |
|        | TSA          | Three-Party Service Allowed                                                                                     | mpo-21             |
|        | TVA<br>TVD   | Trunk Verification Allowed<br>Trunk Verification Denied                                                         | basic-1<br>basic-1 |
|        | UCC<br>UDI   | Unrestricted from Receiving Collect Calls<br>Unrestricted from receiving DID calls                              | supp-10            |
|        | ULAA<br>ULAD | User Level Access Allowed for set based administration<br>User Level Access Denied for set based administration | adminset-21        |
|        | UNR          | Unrestricted                                                                                                    | basic-1            |

# LD 81

| Prompt | Response      | Comment                                                      | Pack/Rel |
|--------|---------------|--------------------------------------------------------------|----------|
|        | USR           | User Selectable Call Redirection key                         | uscr-19  |
|        | USRA          | User Selectable Call Redirection allowed                     |          |
|        | USRD          | User Selectable Call Redirection denied                      |          |
|        | UST           | Telephone Status feature                                     | iap3p-13 |
|        | VCC           | Voice Call to phantom DN                                     | basic-1  |
|        | VCE           | Voice set                                                    | basic-5  |
|        | VDN           | LOGIVOX telephone Volume Down                                | supp-10  |
|        | VMA           | Server Voice Messaging Allowed                               | cs1-8    |
|        | VUP           | LOGIVOX telephone Volume Up                                  | supp-10  |
|        | WTA           | Warning Tone Allowed                                         | basic-1  |
|        | WTD           | Warning Tone Denied                                          |          |
|        | WUK           | Guest entry of Automatic Wake Up key                         | gewu-16  |
|        | XFA           | Call Transfer Allowed                                        | basic-1  |
|        | XFD           | Call Transfer Denied                                         |          |
|        | XHA           | Exclusive Hold Allowed                                       | dhld-4   |
|        | XHD           | Exclusive Hold Denied                                        |          |
|        | XRA           | Ring Again Allowed                                           | optf-1   |
|        | XRD           | Ring Again Denied                                            |          |
| LSNO   |               | List Number.                                                 | basic-1  |
|        | 0-253 0-253   | One Speed Call List Number or a range of list numbers        |          |
|        | 0-8190 0-8190 |                                                              |          |
|        |               | List Number : Release 13 and later                           |          |
|        | <cr>          | Print all lists.                                             |          |
|        |               | LSNO is prompted when FEAT is SCL, SCU, SCC, SSC, SSU or CS. |          |
| NACT   |               | Next Activity                                                | odas-1   |
|        | (NO)          | Return to REQ prompt.                                        |          |
|        | YES           | Print current system data and exit overlay.                  |          |
|        | END           | Exit Overlay program.                                        |          |



| Prompt | Response      | Comment                                                                                          | Pack/Rel |
|--------|---------------|--------------------------------------------------------------------------------------------------|----------|
| NCOS   |               | Network Class of Service. NCOS is prompted when FEAT = COS or NCOS.                              | basic-1  |
|        | 0-3 0-3       | One NCOS group number or a range of group numbers when CDP equipped                              |          |
|        | 0-7 0-7       | One NCOS group number or a range of group numbers when BARS or NFCR equipped                     |          |
|        | 0-15 0-15     | One NCOS group number or a range of group numbers when NARS equipped                             |          |
|        | 0-99 0-99     | One NCOS group number, or a range of group numbers for all features (Release 13 and later)       |          |
| PAGE   | (NO) YES      | Data printed on a per page basis                                                                 | basic-1  |
| REQ    |               | Request                                                                                          | basic-1  |
|        | CNT           | Print a count of telephones equipped with the features specified in response to the FEAT prompt. |          |
|        | END           | Exit Overlay program.                                                                            |          |
|        | LST           | List telephones equipped with the features specified in response to the FEAT prompt.             |          |
| RNPG   |               | Ringling Number Pickup Group.                                                                    | basic-1  |
|        | 0-255 0-255   | One Ringling Number Pickup Group number or a range of group numbers                              |          |
|        | 0-4095 0-4095 |                                                                                                  |          |
|        | <cr>          | Ringling Number Pickup Group : Release 13 and later<br>Print all groups.                         |          |
|        |               | RPNG is prompted when FEAT = RNP, RNPK, PUA, PUD, DPU, DPUA, DPUD, GPU, GPU A or GPUD.           |          |
| SGRP   |               | Station Group                                                                                    | sar-20   |
|        | 0-999 0-999   | One station group number or a range of station group numbers                                     |          |

